

DIGITAL LIGHTING CONTROLLERS INSTRUCTION

Introduction of Multifunction Remote Controller & Simplified Remote Controller:

Power: AAA battery×2; **Communication Protocol:** RF-2.4G; **Effective Distance:** 20M (Without Obstacle)

Number of controllable lamps: 1 controller can control 99 groups of lamps, and no limit to the number of lamps in one group.

ID of Lamp: ID of lamps could be 1 to 99.

Multifunction: ON /OFF, Dimming and Color-temp adjusting,timing ON /OFF, 2 scenes recall,auto dimming,night light.

Copy the ID of Remote Controller: Every remote controller has its ID number.One controller can copy and use the ID number of another controller to control the same lamp, and recover its initial ID number.

Operating method:

Steps of Setting ID number of lamps:

- ①Turn OFF the lamp by switch for 3 Seconds, then turn on lamp, finish step②,③ within 10 Seconds
- ②Press 1 or 2 numbers on the number keys of remote controller, than press “ID” key;
- ③Repeat step ② again in case of mistake, then the lamp will flash 1 time.
- ④Turn off the lamp by switch within 10 seconds, then finish setting.

Control the lamps:

The function of the keys: as the picture on the right.

Control the single group: press the ID number of the lamp you want to control and then press one functional key(on/off, color temp, brightness).

All-control Model: press “ALL” key to control all groups.

TIMING ON/OFF:

Press the ID number of the lamp you want to set, press “ID” key.

SET: Press the number key 1-99, press “☀” timing ON key or “☾” timing OFF key, then finish setting. Timing units is 10minutes.

Cancel: Press “0” key, then “☀” timing ON key or “☾” timing OFF key to cancel timing mode.

COPY THE ID OF CONTROLLER:

Press “S” key of one controller and “I” key of another controller at the same time, keep 6 seconds, the indicator will flash 3 times, then finish setting.

Recovery: Press the “S” key and “ALL” key of the controller which the ID has been copied for 6 seconds, the indicator will flash 3 times.

NIGHT LIGHT MODE:

Press “*” key when the lamp is turned off by the controller to enter the night light mode.

CIRCLE MODE:

Press the ID of the lamp, then press “☉☽☀☾” (left, right, up, down) to enter the circle mode.

SCENE MODE: The system can save two scenes: “A” and “B”

Save:

- ①Adjust the light as your preference.
- ②Press the ID number of the lamp.
- ③Press “ID” key and then press “A” or “B”, the lamp will flash 1 time, then the scene will be saved.

Recall:

- ①Press the ID number of the lamp.
- ②Press “A” or “B”, the lamp will enter the scene you preset.

